

Digitrax Power Supplies Specification Sheet

PS514 70W AC Power Supply



Input	Universal AC 95-240V 50/60 Hz
Slide Switch Selectable	Yes
Selectable Output Voltages	12V, 13.8V, 15V, 16.8V, 19V, 20V, 24V DC Output
Power Interface	US to IEC 2-Pin Grounded Cord Set
Power Indicator	Yes
Over Current and Overload Protection	Yes
Certificate of Conformity	Yes, FCC, RoHS, CE for EM compatibility and IEC 60950 safety requirements Meets MEPS III "green" efficiency standards
Digitrax Product Compatibility	5 Amp Command Stations/Boosters

Prod Date	11/12/2011	Discontinued	Current	Replaced By	Current
MSRP	US\$59.00			SKU	

Digitrax, Inc. is not responsible for unintentional errors or omissions in this document.

Note: For DCS100/DB150 Minimum input should be: 12 volts AC or 15 volts DC.

Note: PS514 should not be used with Zephyr or Zephyr Xtra Starter Sets. The PS314 supplied with the Zephyr Xtra or equivalent supply should be used with Zephyrs.

Note: PS514 should not be used with DCS200 or 8 amp starter sets. These should use the PS2012 or other power supply that can supply 8 amps.

Use the BLUE adapter plug to connect to the provided 2 wire cable for the DCS100 and DB150 Command Station/Boosters.