

Digitrax Command Station Specification Sheet

DCS52 Zephyr Express: All-in-one Command Station/Booster/Throttle



Power Input (DC ONLY)	13.8 VDC
Screen	2.4" LCD
Maximum Output Current	3.5 Amps
Locomotive Addresses	20
Throttle Support	20
Programming Track	Yes, Separate
Program read/write	Yes
Stationary Decoder Addresses	2000+
2 & 4 Digit Addressing	Yes, (address range 9999)
Function Control	30 (F0Fwd, F0Rev and F1-F28)
Consisting	Yes, UniVersal or Advanced
Speed Steps	14,28,128

Prod Date	01/03/2019	Discontinued	Current	Replaced By	Current
MSRP	US\$245.00			SKU	

Option Switch #	Effect on System operation	Factory Default
OpSw 36	Closed = Clears all mobile decoder info & consists	Thrown
OpSw 39	Closed = Clears all internal memory states	Thrown
OpSw 40	Closed = Clears all internal memory states and sets DCS52 to Factory Default	Thrown
OpSw 83	Thrown = DCS52's Jump Mode Disabled	Thrown
	Closed = DCS52's Jump Mode Enabled	

Digitrax, Inc. is not responsible for unintentional errors or omissions in this document.